

TRANSFORMER COMPATIBILITY MR16

Legend						PARATHOM PRO MR16 20 36°	PARATHOM PRO MR16 35 36°	PARATHOM PRO MR16 43 36°	PARATHOM DIM MR16 20 36°	PARATHOM DIM MR16 35 36°	PARATHOM DIM MR16 50 36°	PARATHOM MR 16 20 NON DIM	PARATHOM MR 16 35 NON DIM	PARATHOM MR 16 50 NON DIM
Good compatibility with indicated number of lamps														
Limited compatibility with indicated number of lamps						EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code
Undesired compatibility						4058075433652 / AC33735 4058075433638 / AC33736 4058075433634 / AC33737	4058075609433 / AC32738 4058075609439 / AC32739 4058075609396 / AC32720	4058075609372 / AC32721 4058075609358 / AC32722 4058075609334 / AC32723	4058075796454 / AC42767 4058075796478 / AC42768 4058075796492 / AC42769	4058075796515 / AC42773 4058075796539 / AC42774 4058075796553 / AC42775	4058075609330 / AC32712 4058075609297 / AC32713 4058075609273 / AC32714	4058075796577 / AC42770 4058075796591 / AC42771 4058075796614 / AC42772	4058075796638 / AC42776 4058075796652 / AC42777 4058075796676 / AC42778	4058075609259 / AC32715 4058075609235 / AC32716 4058075609211 / AC32717
Not tested														
Electric Transformers						Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET	Number of Lamps on ET
Brand	Model	Type	Voltage	Wattage										
OSRAM	HTM 70/230-240	ET	230-240, 50-60Hz	20-70W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	HTM 105/230-240	ET	230-240, 50-60Hz	35-105W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	ET-Parrot 70/220-240 I	ET APAC	220-240, 50-60Hz	20-70W		1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	ET-Parrot 105/220-240 I	ET	220-240, 50-60Hz	35-105W		1-4	1-4	2-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	ET-A 60/220-240	ET APAC	220-240, 50-60Hz	20-60W		1-4	1-4	1-4	1-4	1-4	1	1-4	1-4	1-4
OSRAM	ET-L 30/220-240	ET APAC	220-240, 50-60Hz	2-30W		1-3	1-3	1-4	1-4	1-3	1-4	1-4	1-4	1-3
OSRAM	HTB 70/220-240	ET	220-240, 50-60Hz	20-70W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	HALOTRNIC HTN75/230-240 I	ET	230-240, 50-60Hz	20-75W	1-6	1-4	1-4	1-4	1-4	1-4	1	1-4	1-4	1-4
OSRAM	HTM 150/230-240	ET	230-240, 50-60Hz	50-150W	2-6	2-4	2-4	2-4	2-4	2-4	1-4	1	2-4	2-4
OSRAM	HTL105/230-240	ET	230-240, 50-60Hz	35-105W	3-6	3-4	3-4	2-4	2-4	3-4	1-4	1-4	1-4	3-4
OSRAM	IZ-A50/240	ET India	240,50-60Hz	50W		1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	IZ-HALD50/220-240	ET APAC	220-240, 50-60Hz	20-50W		1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	HTB 105/220-240	ET	220-240, 50-60Hz	35-105W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	ET-Parrot 150/220-240 I	ET	220-240, 50-60Hz	50-150W	no	2-4	2-4	2-4	1-4	2-4	1-4	1-4	1-4	2-4
OSRAM	ET-ZE 60/220-240	ET	220-240, 50-60Hz	20-60W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
OSRAM	HTL225	ET	220-240,50-60Hz	50-225W	3-6	2-4	2-4	2-4	3-4	2-4	1-4	1-4	1-4	2-4
OSRAM	OT 15/220-240/12 P	OT	220-240,50-60Hz	15W	1-2		1-4	1-4	1-4		1-4	1-4		
OSRAM	OT 30/220-240/12 P	OT	220-240,50-60Hz	30W	1-4	1-3	1-3	1-4	1-4	1-3	1-4	1-4	1-4	1-3
OSRAM	OT 60/220-240/12 P	OT	220-240,50-60Hz	60W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
SLV	461060	ET	230,50-60Hz	10-60W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
BLOCK	HES 70K	ET	230-240,50-60Hz	20-70W	1-6		1-4	1-4	1-4		1-4	1-4		
BLOCK	HES 105K	ET	230-240,50-60Hz	35-105W	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
EVN	TAB 70 (3310)	ET	230,50-60Hz	20-70W	2-6	2-4	2-4	1-4	1-4	1-4	1	no	2-4	2-4
EVN	MINJOKER 70(T27/10)	ET	230-240,50-60Hz	10-60W	1-6		2-4	2-4	2-4	2-4	1-4	1-4	1-4	
EVN	CLOU 60(T41/09)	ET	230-240,50-60Hz	10-70W	3-6	1-4	1-4	2-4	2-4	1-4	1-4	1-4	1-4	1-4
Berker	Igel 20-105w 2921	ET	230-240,50-60Hz	20-105W	2-6	1-4	1-4	2-4	2-4	1-4	1-4	1-4	1-4	1-4
Berker	SNT 70/QU 2918	ET	230,50-60Hz	20-70W	3-6	1-4	1-4	1-4	1-3	1-4	1-4	1-3	1-4	1-4
Berker	SNTF II 35-105W 2927	ET	230,50-60Hz	35-105W	4-6	2-4	2-4	4	3-4	2-4	2-4	1-2	1	2-4
TCI	SHARK60	EU	220-240,50-60Hz	10-60W	2-6									
TCI	PUMA 105	EU	230-240,50-60Hz	20-105W	2-6									
TCI	ROUND 70	EU	230,50-60Hz	20-70W	2-6									
TCI	MW70 LED	ET	220-240,50-60Hz	10-60W		1-4	1-4				1-4			1-4
Paulmann	Disc electronic S 70	ET	230,50-60Hz	20-70W	3-6	no	no				no			no
Paulmann	Profi 80	ET	220-240,50Hz	20-80W	3-6	2-4	2-4				2-4			2-4
Paulmann	Mipro 70	ET	230,50-60Hz	20-70W	2-6	2-4	2-4	1-4	2-4		2-4	1-4	1-4	2-4
JUNG	SNT 70 F	ET	230,50-60Hz	20-70W	2-6	1-4	1-4	1-4	1-4	2-4	1-4	1-4	1-4	1-4
JUNG	SNT 105 F	ET	230,50-60Hz	20-105W	3-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4
nobile	EN-80F	ET	230,50-60Hz	20-80W	1 & 3-6	2-4	2-4	1-4	1-4	1-4	2-4	1-4	1-4	2-4
nobile	EN-60D2	ET	230,50-60Hz	20-60W	2-6	2-4	2-4	1-4	1-4	1-4	2-4	1-4	1-4	2-4
FN LIGHT	TL105S 20-105W 461107	ET	230-240,50-60Hz	20-105W	1-6	1-4	1-4	1-2	1	1-4	1-4	1-4	1-4	1-4
goodbay	SET110LV(35-110W)	ET	220-240,50Hz	35-110W	2-6	1-4	1-4	1-4	1-4	1-4	1-4	4	1-4	1-4
PHILIPS	Primaline 70 230-240	ET	230-240,50-60Hz	20-70W	2-6	2-4	2-4	1-4	1-4	1-4	2-4	1-4	1-4	2-4
abi	SET210(50-210VA) ALS0476	ET	220-240V, 50Hz	50-210VA	1-6	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4	1-4